

Specification

150W LED grow light



1. Product features:

1).150W LED grow light can replace triple to five times power of HID light, save about 80% energy.

2).Air aviation plug type is applied for power supply connection, it's more convenient to be disassembled, higher grading and more humanized design to compare with traditional fixed connection.

3)Different ratio and spectrum can be customized. Red 620-630nm & 640-660nm, Blue 450-460nm & 460-470nm is recommended to apply. Red stimulate germination, flowering and fruiting while blue promote leafing. Combination of red ,blue,orange,white,yellow color can be provided for plants.

4)Built-in fans in good for heat-dissipation

5) Built-in power supply, no need other device, directly plug AC85V~264V. No need for ballast,reflector.

6) .Ideal device for different stages of plant growth, work well with indoor garden, water solution culture and soil culture plants.


7) . The lighting area will change to different plants and environment, parameters will change as well.

8) .All applied material meet the requirements of environmental protection, no harmful substances as Mercury.

2. Technical parameter:

150W LED grow light parameter

Content	Value	Content	Value
Size	330*330*60mm	Rated power	150W (150x1W)
Input Voltage	AC85~264V	lux	1M/1450,1.5M/690,2M/390
Working current	300mA	Lifespan	50,000 h
Working frequency	50/60 Hz	Color	Red/Blue/Orange/IR/UV
Working condition	-20°-40°	Lighting Area	7M ² /3m
Inner Box	428*428*140mm/1PCS	Gross Weight	5.8kg/pc
Carton Box	435*435*296/2PCS	Gross Weight	12.456kg/2pcs



4. Notice:

- 1).Do work under normal environment.
- 2).Do not touch or beat the light when working.
- 3).None waterproof,do not drip the water in.
- 4).The above specification is on the basic of red and blue 8:1.Any ratio could be customized.